

QuickNet™ Plug Pack Housings

QuickNet™ Plug Pack Housings facilitate quick and easy connection and removal of patch cords from a variety of switches, reducing the time and cost associated with installing and maintaining structured cabling links. Innovative design features of the plug pack allow multiple patch cords to be installed simultaneously with one hand for speed of deployment. Modular plugs are extended forward, eliminating interference with the front bezels of many switches. Individual cable links can be removed without disrupting service to the other network connections. QuickNet™ Plug Pack Housings accept all Panduit® UTP, and shielded Category 6A/6 copper patch cords.



Key Features

Benefits

Compatible with most RJ45 48-port, 1 RU switch blades and chassis including Cisco* Catalyst and Nexus series switches	Utilizes precision geometry for quick connection to the switch; standard, QPPN version compatible with Cisco* Catalyst 6K, 4K, and now 3750 and 3560 series switches; QPPNR recessed version compatible with Cisco* Nexus 7K series switches.
Integrated finger latch	Enables quick, one-handed installation and removal of QuickNet™ Plug Pack Assemblies from the switch
Variety of configurations	Available in six, eight, or twelve cable assemblies for optimal switch compatibility
Modular design	Snaps modular plugs directly into switches and utilizes an integral release tab to ensure easy on-site moves, adds, and changes
Low profile design	Allows plug pack assemblies to be installed side by side or stacked on top of each other providing maximum port density in high density installations
Marker ties (optional)	Enables easy identification in high density installations; provides additional level of security when combined with optional lock-in device
Removal tool (optional)	Allows individual patch cords to be removed without disrupting other network connections
Lock-in device (optional)	Prevents unauthorized removal of patch cords from the switch for an additional level of security

Application Information

Switch blades periodically need to be replaced or exchanged due to system upgrades or repair/replacement. Due to high port density, removing and re-connecting each individual patch cord is time consuming. Each QuickNet™ Plug Pack Housing accepts six, eight or twelve Panduit patch cords, allowing them to be installed, disconnected, and re-connected quicker than traditional methods, resulting in a 67% improvement of mean time to repair.



Optional lock-in device and marker ties provide an additional level of network security.



Optional labels allow each assembly and port to be identified.

*Cisco is a registered trademark of Cisco Technology, Inc.

QuickNet™ Plug Pack Housings














Ordering information

Part Number	Description	Std. Pkg. Qty.	Std. Ctn. Qty.
QuickNet™ Plug Pack Housings			
QPPN6++	QuickNet™ Plug Pack Individual Housing accepts six Panduit RJ45 patch cords.	1	10
QPPN8++	QuickNet™ Plug Pack Individual Housing accepts eight Panduit RJ45 patch cords.	1	10
QPPN12++	QuickNet™ Plug Pack Individual Housing accepts twelve Panduit RJ45 patch cords.	1	10
Recessed QuickNet™ Plug Pack Housings			
QPPNR6S	QuickNet™ Plug Pack Individual Recessed Housing accepts six Panduit RJ45 patch cords. Compatible with Cisco Nexus 7000 Series Switch.	1	10
Accessories			
QPPRT	Removal tool allows individual patch cords to be removed without disruption of other network connections.	1	10
QPPLD6-X	Lock-in device prevents unauthorized removal of patch cords from the 6 and 12 plug pack assembly. (Recommended installed quantity two per 6-pack, four per 12-pack).	1	100
QPPLD8-X	Lock-in device prevents unauthorized removal of patch cords from the 8 plug pack assembly. (Recommended installed quantity two per 8-pack).	1	100

Order in multiples of Standard Package Quantity.

++ Available in BU (Blue), BL (Black), RD (Red) or WH (White). Recessed version, part number QPPNR6S, is silver.

QuickNet™ Plug Pack Compatibility

Switch Brand and Model*	Switch Port Configuration	Type of Plug Pack	Plug Pack Part Number	Color Options (++)			
				BL	BU	RD	WH
Cisco Catalyst and Nexus 2000 – 6000 series (including 2960, 3560, 3750, and 4510 models)	6 / 12 Port Groups 	6-Position	QPPN6++				
		12-Position	QPPN12++	BL	BU	RD	WH
Other Brands and Models (compatibility varies, see below)	8 / 16 Port Groups 	8-Position	QPPN8++				
				BL	BU	RD	WH
Cisco Nexus 7000 series (including 7009 and 7010 models)	6 / 12 Port Groups 	6-Position Recessed	QPPNR6S	 S (Silver only)			
	8 / 16 Port Groups 			N/A			

*Note: Due to ongoing updates of switch models, compatibility of QuickNet™ Plug Pack to a specific switch should be confirmed through test fitting with an actual Plug Pack. Contact your Panduit sales representative for a sample.



12-Position Plug Pack



QuickNet™ Removal Tool



QuickNet™ Lock-In Device



Copper Patch Cords are available in a variety of lengths and colors

WORLDWIDE SUBSIDIARIES AND SALES OFFICES

PANDUIT CANADA
Markham, Ontario
cs-cdn@panduit.com
Phone: 800.777.3300

PANDUIT EUROPE LTD.
London, UK
cs-emea@panduit.com
Phone: 44.20.8601.7200

PANDUIT SINGAPORE PTE. LTD.
Republic of Singapore
cs-ap@panduit.com
Phone: 65.6305.7575

PANDUIT JAPAN
Tokyo, Japan
cs-japan@panduit.com
Phone: 81.3.6863.6000

PANDUIT LATIN AMERICA
Guadalajara, Mexico
cs-la@panduit.com
Phone: 52.33.3777.6000

PANDUIT AUSTRALIA PTY. LTD.
Victoria, Australia
cs-aus@panduit.com
Phone: 61.3.9794.9020

For a copy of Panduit product warranties, log on to www.panduit.com/warranty

For more information

Visit us at www.panduit.com

Contact Customer Service by email: cs@panduit.com
or by phone: 800.777.3300



©2013 Panduit Corp.
ALL RIGHTS RESERVED.
COCB14--WW-ENG
Replaces WW-COCB24
12/2013