



MP300 PRINTER

Quick Reference Card



Printer Tech Support 1-866-871-4571
GA-TECHSUPPORT@PANDUIT.COM
Rev. 3.8 - 10/12/22



414376700

1

MP300 Printer and Accessories

Part No.	Description
MP300	Includes MP300 printer, 1 cassette of S100X150VAM, hard carrying case, Li-Ion rechargeable battery pack, magnetic attachments, USB cable, and power adapter (MP300-AC). For use in North America
MP300/E	Includes MP300 printer, 1 cassette of S100X150VAM, hard carrying case, Li-Ion rechargeable battery pack, magnetic attachments, USB cable, power adapter (MP300-AC) and international power cord(s). For use outside of North America
MP300-ACS	120-240 VAC universal power adapter module with power cord for North America.
MP-BATT	Replacement Li-Ion rechargeable battery pack
MP-CASE	Replacement hard carrying case

MP300 Label Cassettes

- Die-cut self-laminating labels, Turn-Tell™ labels, flag labels, marker plates, nylon cloth, polyester, and network component labels
- Continuous heat-shrink tubing and continuous tapes

2

Label Cassette Types


Label Material	Example Part Number	Typical Application
Self-Laminating	S100X150VAM	Wire/Cable marking
Turn-Tell™	R100X150V1M	Wire/Cable marking
Heat Shrink	H000X044H1M	Wire/Cable marking
Marker Plates	M300X050Y6M	Wire/Cable marking
Flag Labels	F100X150AJM	Wire/Cable marking
Nylon Cloth	N100X125C1M	Wire/Cable marking
Nylon Cloth Tape	T100X000C1M-BK	Wire/Cable marking
Adhesive Polyester	C200X100YJM	General component labeling
Polyolefin	C252X030FJM	Network infrastructure
Polyolefin Tape	T038X000FJM-BK	Terminal blocks
Colored Vinyl Tape	T100X000VXM-BK	Safety/Facility
Colored Polyester Tape	T100X000BXM-BK	Safety/Facility

Note: Please check Panduit website for the latest firmware.

3

Getting Started

- Included Items




- Install Li-ion battery



- Charge Li-ion battery




- Install label cassette



4


MP300 Display



- Label Mode
- Current label length & width
- CAPS Lock on
- Page Number
- Line Number
- Cursor
- Label Part number
- Battery Life
- Font Size
- Cutter Setting

5

MP300 Keypad Functions



6


- Feed and cut the label material
- Label exit slot
- Print a label
- Display Screen
- Number and letter keys
- Shift/secondary functions
- Enter a character with an accent
- CAPS lock
- Create a serialization
- Create a barcode
- Create a symbol
- Directional arrow keys
- Enter key
- Add a page/print preview
- Set label margins
- Set tape length/rotate text
- Text options key
- Change font size
- Space bar
- Label mode keys
- Delete/Clear key
- Power on/off
- Setup menu key
- File save and recall

7

Label Modes




- Wiremarker




- Component



- Wrap



- Flag



- Tape




- Vertical




- Mixed Length



- Terminal Block



- Network




8

HOW TO: Serialization

ADV.
123 SERIAL

1. Type "1A-A"
2. Press the SERIAL key
3. Enter a start value of 01, end value of 02, and increment value of 1
4. Press ENTER
5. Press PRINT

Example using S100X150VAM, self-laminating wire/cable markers:



9

Symbols



1. Press the SYMBOL key
2. Select the symbol group named WARNING
3. Select the ⚠ symbol on the first row
4. Press ENTER
5. Press SPACE
6. Type "CAUTION"
7. Press PRINT

Example using T100X000VXM-BK, black on yellow continuous vinyl tape:



Over 20 categories of symbols for electrical, network, audio visual, laboratory, arc flash, PPE, Prohibition, arrows, and more.

Hundreds of individual images included.



10

Barcodes



Code 39

1. Press the BARCODE key
2. Scroll to CODE 39 and press ENTER
3. Select Medium Width
4. Select 2.5 Ratio
5. Select check digit OFF
6. Type text ABC
7. Press ENTER
8. Press PRINT



QR Code

1. Press the BARCODE key
2. Scroll to QR CODE and press ENTER
3. Select 7% ECC Level
4. Type text WWW.PANDUIT.COM
5. Press ENTER
6. Press PRINT





9 different barcode styles included

11

Print from Easy-Mark Plus Software

- Connect the MP300 printer to a computer with USB cable.
- Print from Easy-Mark Plus Labeling Software. Easy-Mark Plus is sold separately and includes MP300 driver.
 - Easy-Mark Plus on disc: EMPLUS-CD
 - Easy-Mark Plus on USB flash drive: EMPLUS-2GO
 - Easy-Mark downloadable version: EMPLUS-DL



12

Other Functions

- PRINT – Print labels
- MULTI – Adjust print options, print copies
- FEED | CUT – Feeds label material without printing. Cuts label after feeding.
- CLEAR – Clear screen, remove formatting
- FILE – Save or recall label files
- FONT SIZE – Change the character size
- TEXT OPTIONS – Change the font styling
- MARGIN – Change the label margin
- LENGTH – Adjust the label length
- ROTATE – Rotate the text
- PAGE – Add a new page to a label design
- PRINT PREVIEW – View the label before printing

13

Setup Menu



- Auto Cut – Turn the Automatic Cut function ON or OFF. If Auto Cut is ON, then select Half Cut ON or OFF. Half Cut cuts through the label but not the liner.
- Print Density – Raise or lower the print density/darkness of print
- Drop Stop – Set the drop stop function to ON or OFF. Drop Stop pauses printing until the cut label has been removed from printer exit.
- Die-cut Position – Adjust the print position in the length and width directions
- Backlight – Turn backlight function ON or OFF
- Language – Select the preferred language. 13 languages are available: Dansk, Deutsch, English, Español, Français, Italiano, Nederlands, Norsk, Português – BR, Português – EU, Suomi, Svenska, Türkçe
- Inch/cm – Change the unit of measure between inches and centimeters
- Version – Display the current operating system version number

14

Additional Support

Visit www.panduit.com

Free Downloads

Path: Support / Download Center / Software
Firmware Printers

- Detailed Operator's Manual
- Replacement Quick Reference Card
- Product Bulletin
- Product Specification and Safety Information
- Latest Printer Firmware

Warranty Registration

Path: Support / Product Registration

Related Products

- MP Label Cassettes
- MP75 Printer
- MP100 Printer
- MP200 Printer
- Mobile Labeling Apps for Android and iOS
- Easy-Mark Plus Labeling Software

Note: Please refer to the instruction label in cassette compartment for the printer head cleaning.

15

Global Customer Service

- cs@panduit.com
- U.S. and Canada: 800-777-3300
- Europe, Middle East, and Africa: 44.20.8601.7200
- Latin America: 52.33.3777.6000
- Asia Pacific: 65.6305.7575

Panduit Technical Support

- GA-TECHSUPPORT@PANDUIT.COM
- U.S. and Canada: 1-866-871-4571
- Europe: 31.546.580.452
- Latin America: 52.33.3777.6000
- Asia Pacific: 65.6379.6700

Part Number: MP300-QRC-EN, Rev. 3.8
DWG Number:00210ECA

16